

590+ Series Product Code

		Block 1	Block 2	Block 3	Block 4
<b>Family</b>		590P 591P	23 2150 1 0	P 00	U 0 A 0
<b>Current/Power Ratings</b>		Supply Voltage	Output Current (A)	Frame Size	
110-220V 3ph			23		
		15	1	2150 1	
		35	1	2350 1	
		40	2	2400 2	
		70	2	2700 2	
		110	2	3110 2	
		165	2	3165 2	
		180	3	3180 3	
		270	3	3270 3	
		380	4	3380 4	
		500	4	3500 4	
		725	4	3725 4	
		830	4	3830 4	
		1580	5	4158 5	
220-500V 3ph			53		
		15	1	2150 1	
		35	1	2350 1	
		40	2	2400 2	
		70	2	2700 2	
		110	2	3110 2	
		165	2	3165 2	
		180	3	3180 3	
		270	3	3270 3	
		380	4	3380 4	
		500	4	3500 4	
		725	4	3725 4	
		830	4	3830 4	
		1580	5	4158 5	
		1250	6	4125 6	
		1600	6	4160 6	
		1950	6	4195 6	
		1200	H	4120 H	
		1700	H	4170 H	
		2200	H	4220 H	
		2700	H	4270 H	
500-600V 3ph			63		
		380	4	3380 4	
		500	4	3500 4	
		725	4	3725 4	
		830	4	3830 4	
		1580	5	4158 5	
500-690V 3ph			73		
		1250	6	4125 6	
		1600	6	4160 6	
		1950	6	4195 6	
		1200	H	4120 H	
		1700	H	4170 H	
		2200	H	4220 H	
		2700	H	4270 H	
<b>Auxiliary Supply</b>		Universal 115V-230V 1ph (Frames 1, 2, 6 & H)		0	
		115V 1ph (Frames 3 - 5)		1	
		230V 1ph (Frames 3 - 5)		2	
<b>Mechanical Style</b>		Panel Mounting		P	
		Panel Mounting + Airflow Kit (option on Frames 4 & 5 only)		A	
<b>Special Option</b>		None		00	
		Documented special options (01-99)			
<b>Destination</b>		English (50/60Hz)			U
		German			D
		Spanish			E
		French			F
		Italian			I
<b>Keypad</b>		None			0
		6901 keypad fitted			4
<b>Speed Feedback</b>		Analog Tacho			A
		Glass Fiberoptic encoder			G
		Plastic Fiberoptic encoder			P
		Armature Voltage			V
		Wire-ended Encoder			W
<b>Comms</b>		None			0
		ControlNet			C
		DeviceNet			D
		Ethernet			E
		Link			L
		ModBus +			M
		CanOpen			N
		Profibus			P
		RS485/RS422			R

### 590+ Frame 6 Phase Assembly Product Code

		Block 1	Block 2	Block 3
		<i>Example</i> ▶ <b>590PL</b>	<b>53 4125 6 0</b>	<b>P 00</b>
<b>Family</b>	590+ Series DC Digital Drive - regen Phase Limb 591+ Series DC Digital Drive - non-regen Phase Limb	590PL 591PL		
<b>Current/Power Ratings</b>	Supply Voltage			
	220-500V 3ph		53	
		1250	6	4125 6
		1600	6	4160 6
		1950	6	4195 6
	500-690V 3ph		73	
	1250	6	4125 6	
	1600	6	4160 6	
	1950	6	4195 6	
<b>Auxiliary Supply</b>	None			0
<b>Mechanical Style</b>	Panel Mounting			P
<b>Special Option</b>	None			00
	Documented special options (01-99)			

HA500530C000\_03

### 590+ Series Frame 6 Control Panel Assembly Product Code

		Block 1	Block 2	Block 3	Block 4
		<i>Example</i> ▶ <b>590PG</b>	<b>53 0000 6 0</b>	<b>P 00</b>	<b>U 4</b>
<b>Family</b>	590+ Series DC Digital Drive - Frame 6 Gantry	590PG			
<b>Current/Power Ratings</b>	Supply Voltage				
	220-500V 3ph		53		
		6		0000 6	
	500-690V 3ph		73		
	6		0000 6		
<b>Auxiliary Supply</b>	Universal 115V-230V 1ph				0
<b>Mechanical Style</b>	Panel Mounting			P	
<b>Special Option</b>	None				00
	Documented special options (01-99)				
<b>Destination</b>	English (50/60Hz) German Spanish French Italian				U D E F I
<b>Keypad</b>	6901 keypad fitted				4

HA500530C000\_03